

Digital Touchpad Controller

Smart touch control in a compact design

MacroAir's Digital Touchpad Controller is compact yet full of functionality. Featuring visual and audible touch feedback, it lets you control on/off, fan speed and forward/reverse operation with the touch of a finger. It even automatically stores the memory of your last used settings and makes repairs faster and easier through on-screen error code diagnostics.

For ultimate fan control and versatility, MacroAir's digital touchpad controller is a smart choice.

AT A GLANCE

- Bright & compact touchpad design
- Visual & audible touch feedback
- Wall or flush mount options
- · Controls: power, direction & speed
- Stores last used settings
- Error code diagnostics & reset capability

KEY SPECIFICATIONS

Y., <u></u>	
CPU	32-bit RISC CPU
LCD	2.8 TFT (Resolution 240 x 320 x 16)
Backlight Life	20,000 hours
Brightness	160 cd/m ²
Touch Panel	Yes
Reset Button	O O Yes
Powered from Terminal Block	+10 - 30 VDC
Power Consumption	1.2 W
Wall mount dimensions (H x W x L)	5.3 in x 3.6 in x 1.6 in [135.5 mm x 91.2 mm x 42 mm]
Flush mount dimensions (H x W x D)	7.8 in x 3.0 in x 0.3 in [199 mm x 76 mm x 7.3 mm]
Operating Temperature	-4 to 158°F [-20 to 70° C]

RESTRICTIONS

AirVolution-D Models 370, 550, 780, AVD3 400 ft Max CAT5E remote cable

> AirVolution, AirSpan, AirEco 200 ft Max CAT5E remote cable

Consult MacroAir if your application requires a NEMA 4X-compliant remote



Learn more at macroairfans.com